

## **DSTV SETTINGS FOR SINGLE VIEW DECODERS ON A ONE CABLE SYSTEM**

Using the remote of the Dstv, press MENU then  
Go to ADVANCED OPTIONS – press OK  
Go to DISH INSTALLATIONS press OK  
Pin code 9949



**Home Network Dstv IS7** - remains as is  
(Frequency should be **11594** and Symbol rate **27500** – **do not change these**)

**Network 2 Dstv IS7** – press OK  
Go to FREQUENCY – press OK  
Left key to remove numbers, then enter **11210** – press OK  
Go to SYMBOL RATE – press OK  
Left key to remove numbers, then enter **30000** – press OK  
Go to USE NIT – right key to **SMATV**  
Go to ACCEPT ALL DISPLAYED VALUES & LEAVE SCREEN

**Network 3 Dstv IS7** – press OK  
Go to FREQUENCY – press OK  
Left key to remove numbers, then enter **11250** – press OK  
Go to SYMBOL RATE – press OK  
Left key to remove numbers, then enter **30000** – press OK  
Go to USE NIT – right key to **SMATV**  
Go to ACCEPT ALL DISPLAYED VALUES & LEAVE SCREEN

**Network 4 Dstv IS7** – press OK  
Go to FREQUENCY – press OK  
Left key to remove numbers, then enter **11290** – press OK  
Go to SYMBOL RATE – press OK  
Left key to remove numbers, then enter **30000** – press OK  
Go to USE NIT – right key to **SMATV**  
Go to ACCEPT ALL DISPLAYED VALUES & LEAVE SCREEN

**Network 5 Dstv IS7** – press OK  
Go to FREQUENCY – press OK  
Left key to remove numbers, then enter **11330** – press OK  
Go to SYMBOL RATE – press OK  
Left key to remove numbers, then enter **30000** – press OK  
Go to USE NIT – right key to **SMATV**  
Go to ACCEPT ALL DISPLAYED VALUES & LEAVE SCREEN

**Network 6 Dstv IS7** – press OK  
Go to FREQUENCY – press OK  
Left key to remove numbers, then enter **11370** – press OK  
Go to SYMBOL RATE – press OK  
Left key to remove numbers, then enter **30000** – press OK  
Go to USE NIT – right key to **SMATV**  
Go to ACCEPT ALL DISPLAYED VALUES & LEAVE SCREEN

**Network 7 Dstv IS7** – press OK  
Go to FREQUENCY – press OK  
Left key to remove numbers, then enter **11410** – press OK  
Go to SYMBOL RATE – press OK  
Left key to remove numbers, then enter **30000** – press OK  
Go to USE NIT – right key to **SMATV**  
Go to ACCEPT ALL DISPLAYED VALUES & LEAVE SCREEN

Go to SCAN ALL NETWORKS

If this did not help, go to FACTORY RESET, then redo above steps.  
Should you experience further problems, please contact your body corporate delegate.